



The PW200 12 Volt DC to AC Power Inverter provides 200 watts of continuous power, with a peak surge of 400 watts.

This unit has the following features:

- Anodized aluminum case which provides durability & maximum heat dissipation.
- Built-in Cooling Fan
- External, Replaceable 30 Amp spade-type Fuse
- 12 volt Cigarette Lighter + Power Plug
- Overload Indicator
- Power ON/OFF Switch

Specifications	
Continued Power	200W
Peak Load Power Rate	< 400W
Overload Output Power	210-240W
No Load Current Draw	< 0.1A
Input DC Voltage Range	10-15.5V
Output Voltage Range	117 +/- 10%
Output Frequency Range	60 +/- 3Hz
Max Outer Temperature	< 65 C
Max Power Efficiency	> 90%
High Voltage Cut Off Level	16.5 +/- 1V
Low Voltage Alarm Level	10.5 +/- 0.5V
Low Voltage Cut Off Level	10 +/- 0.5V
Short Protect	Yes
Overload Protect	Yes
Dimension (LxWxH) in	5.59 x 5 x 2
Weight	3.0 lbs
Standard Test Voltage Input	DC 12V