



The PW3500 12 Volt DC to AC Power Inverter provides 3500 watts of continuous power, with a peak surge of 7000 watts.

This unit has the following features:

- Anodized aluminum case which provides durability & maximum heat dissipation.
- Built-in Cooling Fan
- Digital Led Display (Input DC Voltage or Output Wattage)
- Overload Indicator
- Power ON/OFF Switch

Specifications	
Continued Power	3500W
Peak Load Power Rate	< 7000W
Overload Output Power	3550-3800W
No Load Current Draw	< 0.5A
Input DC Voltage Range	10-15.5V
Output Voltage Range	117 +/- 10%
Output Frequency Range	60 +/- 3Hz
Max Outer Temperature	< 65 C
Max Power Efficiency	> 90%
High Voltage Cut Off Level	15.5 +/- 1V
Low Voltage Alarm Level	11 +/- 0.5V
Low Voltage Cut Off Level	10 +/- 0.5V
Short Protect	Yes
Overload Protect	Yes
Dimension (LxWxH) in	19.92 x 8.9 x 6.1
Weight	21 lbs
Standard Test Voltage Input	DC 12V